





トルク調節機能無しタップアダプター

RA



	タップ範囲	$\phi D1$	$\phi D2$	L1	L2
RA1	M3~M12	19.0	32.0	21.5	7.0
RA2	M8~M24	31.0	50.0	35.0	11.0
RA3	M14~M36	48.0	72.0	55.5	14.0



タップ (JIS規格)

メートルネジ D	ユニファイネジ D	管用ネジ D	軸径 $\phi d1$	角部幅 K	角長 Ho	タップアダプター		
						シリーズ#1	シリーズ#2	シリーズ#3
M3	U No.5・U No.6		4.0	3.2	6.0	RA1J-M03		
M4	U No.8		5.0	4.0	7.0	RA1J-M04		
M5	U No.10・U No.12		5.5	4.5	7.0	RA1J-M05		
M6	U 1/4		6.0	4.5	7.0	RA1J-M06		
M7-M8			6.2	5.0	8.0	RA1J-M08	RA2J-M08	
M9-M10	U 3/8		7.0	5.5	8.0	RA1J-M10	RA2J-M10	
M11	U 7/16	P 1/16・P 1/8	8.0	6.0	9.0	RA1J-M11	RA2J-M11	
M12			8.5	6.5	9.0	RA1J-M12	RA2J-M12	
M14-M15	U 9/16		10.5	8.0	11.0		RA2J-M14	RA3J-M14
M16			12.5	10.0	13.0		RA2J-M16	RA3J-M16
M18	U 3/4	P 3/8	14.0	11.0	14.0		RA2J-M18	RA3J-M18
M20			15.0	12.0	15.0		RA2J-M20	RA3J-M20
M22	U 7/8		17.0	13.0	16.0		RA2J-M22	RA3J-M22
M24-M25		P 5/8	19.0	15.0	18.0		RA2J-M24	RA3J-M24
M26-M27	U 1		20.0	15.0	18.0			RA3J-M27
M30		P 3/4	23.0	17.0	20.0			RA3J-M30
M33			25.0	19.0	22.0			RA3J-M33
M36-M38		P 1.1/8	28.0	21.0	24.0			RA3J-M36